



K-1/K-2 Smart Light Control Switch

Ansee K series Smart Light Control Switch replaces a standard light switch in your home and can be controlled remotely with an Android/IOS smart phone or tablet or by touch the switch, which allows you to turn lights on and off from anywhere. Remote control function is available after connecting the switch with AX-360 IP Camera. By working with AX-X03 series alarm host, the switch can turn on light automatically after once receiving alarm signals.

Features



Short circuit and over current protection



Smart Dimmer Control (Optional)



Remote control through cellphone



Linkage function with alarm host



Touch faceplate

Specifications

Model	K-101	K-101T	K-102	K-103	K-201	K-201T	K-202	K-203
Port	Single Live Wire (L)				Single Neutral Wire (N)			
Adjust Light(Y/N)	N	Y	N	N	N	Y	N	N
Load Path	Single	Single	Double	Three	Single	Single	Double	Three
Load Format	Osram Lamp, Efficient Light Bulb, LED Lamp etc.							
Minimum Load	6W							
Maximum Load	300W Each							
Input Voltage Tolerance	90-260VAC							
Measurement	86*86*32. 8 mm , Toughened Glass Panel							

Ansee Co. Ltd

Add: Building A, GuanLong First Industry Park,
XiLi Town, NanShan District, Shenzhen, China
(518055)

Tel: 0755-86521099/86522966

Fax: 0755-26984949

Email: sales@anseetec.com

Web: www.anseetec.com