



Smart Energy Plug In Switch

Smart Plug In Switch koji omogućava podešavanje radnog vremena za potrošače sa osvrtom na Vaše potrebe. Laka instalacija i niska potrošnja energije sa izvještajima o potrošnji energije povezanog uređaja.

Jednostavan Plug-and-play Zipato Smart Plug-in switch Vam omogućava da kontrolišete utičnice pomoću Zipato kontrolera za kućnu automatizaciju ili bilo kojeg drugog Z-Wave kontrolera, ili tastera na samom Plug-in uređaju. Može podnijeti otpornička opterećenja do 13A. Šalje Vam izvještaje o naponu, struji, koeficijentu snage, trenutnoj snazi i akumuliranoj potrošnji. Doprinosi uštedama energije.

KARAKTERISTIKE

- Pametni Energy Plug-In prekidač omogućava podešavanje radnih sati za potrošače, osvrćući se na Vaše potrebe
- Šalje izvještaje o naponu, struji, koeficijentu snage, trenutnoj snazi i akumuliranoj potrošnji
- Otporničko opterećenje 13A
- Zero-crossing switch
- Automatski izvještaj o Vataži (Wattage) kada varijacija pređe 5%
- LED indikacija potrošnje energije
- Zaštita od preopterećenja
- Veoma niska potrošnja energije
- Over-the-air firmware update
- Lak za montirati – Plug-In



TEHNIČKE SPECIFIKACIJE

PROTOCOL:

Z-Wave Plus

OPERATING CONDITIONS:

OPERATING VOLTAGE: 100 ~ 240VAC
/50Hz/60Hz

MAXIMUM LOAD: 13A (Resistive load)

OPERATION TEMPERATURE: 0°C ~ 40°C

RANGE:

up to 40 meters indoor

up to 70 meters outdoor

DIMENSIONS

DEVICE DIMENSIONS: 79 x 51 x 18 mm

DEVICE WEIGHT: 107g

PACKAGE DIMENSIONS: 89 x 82 x 127
mm

PACKAGE WEIGHT: 159g

REGULATION:

Low Voltage Directive 2014/35/EU

EMC Directive 2014/30/EU

R&TTE 1995/5/EC

LED INDICATION FOR POWER

CONSUMPTION

Blue – 59W and bellow

Cyan – 60W ~ 119W

Green – 120W ~ 399W

Orange – 400W ~ 799W

Pink – 800W ~ 1199W

Red – 1200W and above

FREQUENCY

ph-pan16.eu 868.42 MHz (EU)

ph-pan16.ru 869.02 MHz (RU)

WARRANTY 1 year standard