



Smart Smoke Sensor

Zipato Smart Smoke Sensor (Z-Wave) je dizajniran da daje rano upozorenje o nastanku požara, oglašavajući ugrađenu alarm svirenu, baziran na Z-Wave tehnologiji. Z*Wave je bežični komunikacijski protocol dizajniran za daljinsku kontrolu potrošala u stambenim automatizovanim domovima ili lakim komercijalnim okruženjima. Ne može detektovati gas, toplotu, plamen, i ne može spriječiti ili ugasiti vatru.

KARAKTERISTIKE

- Novi Z-Wave 500 series čip omogućava brži prenos podataka višekanalni rad i brži prenos podataka
- Zvučna i Z-Wave upozorenja o detektovanom dimu
- Ugrađen zvučni alarm
- Veoma niska potrošnja energije
- Automatski izvještaj o niskom nivou baterije
- Laka instalacija i premještanje

TEHNIČKE SPECIFIKACIJE

OPERATING CONDITIONS:

OPERATING VOLTAGE 3V

ALARM CURRENT 60 mA

STANDBY CURRENT 20 uA

OPERATION TEMPERATURE -10°C ~ 50°C

ALARM SOUND

85Db (1m distance)

PROTOCOL Z-WavePlus

POWER CR123A, 1400mAh

RANGE up to 30 meters indoor

up to 70 meters outdoor (designed for indoor use only)

DIMENSIONS

DEVICE DIMENSIONS: 60 x 60 x 50 mm

DEVICE WEIGHT: 132g

FREQUENCY

hm-hs1sa-z.eu 868.42 MHz (EU)

REGULATION

Directive 2014/53/EU

CE

RoHS

WARRANTY 1 year standard